

SERIES BM1000

BM1000P



WEIGHT	1,5 kg
DIMENSIONS	23 X 18 X 22 cm
PACKING VOLUME	0,009 m³

GROUP

SERIES BM1000

BM1000P

CHARACTERISTICS

- To work on the wall or on the table.
- Protection IP54.
- 6-digit 25 mm high LCD display with backlighting.
- 7-key multifunction keyboard: ON / OFF, GROSS / NET, ZERO, TARE, PRINT and TOTAL.
- Automatic and cumulative tare reset.
- Tare fixing and count pieces function.
- 2 RS 232 communication ports.
- Possibility to connect to or function as a weight repeater.
- Multiple pre-configured tickets.
- Power supply 115 V or 230 V AC.

Model Relays (I/O)

- 4 Solid State Relay outputs.
 - Up to 230V AC/DC and 100mA driving capability;
 - Can be configured as OFF, NO, NC or timed Pulse;
 - Action triggered by weight value.
- 4 Opto Isolated Inputs.
 - Up to 30V DC input levels.
- 4-20mA Current Loop.
 - Independent Min and Max freely defined by weight values at setup;
 - Min and Max levels fine tune at setup.

MODEL

REFERENCE

BM1000P

20433440200J

BM1000P BAT

20433440300J

BM1000P AC

20433440000J

BM1000P AC BAT

20433440100J

BM1000P AC RELAYS

20433440012J

OPTIONS

REFERENCE

Ethernet + Wifi

20756020000A

RGB Levels LED



20709210000A

Siren warning sound



20765010000A

Swivel wall bracket



20716240000B

See the price list



www.balancasmарques.com
facebook.com/balancasmарques

HEAD OFFICE

Edifício Balanças Marques
Parque Industrial de Celeirós, 2ª Fase
Apart. 2376
4701-905 Braga - PORTUGAL

LISBON SUPPORT CENTER

Rua Actriz Adelina Fernandes 15A Dto.
2795-005 Linda-a-Velha
Lisboa - PORTUGAL

T +351 253 309 830
F +351 253 672 882
email internacional@balancasmарques.pt